

ТАБЛИЦА СООТВЕТСТВИЯ ТРАНСФОРМАТОРОВ И СВЕТИЛЬНИКОВ



| Мин – Макс нагрузка | | 10 Вт – 60 Вт | | 10 Вт – 60 Вт | | 35 Вт – 105 Вт | | 20 Вт – 105 Вт | | 50 Вт – 150 Вт | |
|---------------------|---------------|---------------|------|---------------|------|----------------|------|----------------|------|----------------|------|
| Светильник | Трансформатор | ET190 B-EKO | | ET190 U | | ET190 K | | ET190 P | | ET190 L | |
| | | мин | макс | мин | макс | мин | макс | мин | макс | мин | макс |
| FT9251 02 | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |
| FT9251 03 | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |
| FT9251 04 | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |
| FT9251 06 | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |
| FT9251 08 | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |
| HWH 9275 04 | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |
| FT9251-T 03 | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |
| FT9251-T 04 | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |
| FT9251-T 08 | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |
| FT9251-TV 04 | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |
| FT9251-TV 08 | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |
| 6101-010 04 | | 1 | 1 | 1 | 1 | 1 | 2 | 1 | 2 | 2 | 3 |
| 6101-010 06 | | 1 | 1 | 1 | 1 | 1 | 2 | 1 | 2 | 2 | 3 |
| 6180-115 02 | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |
| MR-11 20W | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |
| MR-11 35W | | 1 | 1 | 1 | 1 | 1 | 3 | 1 | 3 | 2 | 4 |
| MR-16 20W | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |
| MR-16 35W | | 1 | 1 | 1 | 1 | 1 | 3 | 1 | 3 | 2 | 4 |
| MR-16 50W | | 1 | 1 | 1 | 1 | 1 | 2 | 1 | 2 | 1 | 3 |
| DS 51S 12V/20W-38 | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |
| DS 51S 12V/35W-38 | | 1 | 1 | 1 | 1 | 1 | 3 | 1 | 3 | 2 | 4 |
| DS 51S 12V/50W-38 | | 1 | 1 | 1 | 1 | 1 | 2 | 1 | 2 | 1 | 3 |
| HALOSTAR 12V/20W | | 1 | 3 | 1 | 3 | 2 | 5 | 1 | 5 | 3 | 7 |